

Radiator, 1x120mm 11-FPI Copper

The copper core HX-120HL provides an approximate 400W of added heat dissipation when coupled with one 120mm fan. With a fin density of 11 FPI (fins per inch), it is optimized for low/quiet air flow. Horizontal G 1/4 BSPP (parallel) thread fitting sockets. BLT-HX025 mounting screw kit included. Dual pass, 15mm (0.59") fan hole spacing, copper fins with brass pipes.

General	
Weight	1.25 lb (0.57 kg)
Wetted Materials	Brass/Copper
Radiators	
Fan Capacity	1 x 120mm
Fins Per Inch (FPI)	11